

POWER INSERTER / SPLITTER

IFP 529

Description:

IFP 529 is intended to power a UFO from a battery (12V / 24V).
IFP 529 is a power inserter in a small white plastic housing intended for indoor "click on" wall mounting.
IFP 529 has F-connectors on all RF in- and outputs.
IFP 529 has one broadband input and two outputs.
IFP 529 has an auto reset fuse.

This product is for indoor use only!!

Electrical data:

| | |
|----------------------------|-----------|
| Input | VHF + UHF |
| Channels | 2-69 + FM |
| Frequency range.....(MHz): | 47-862 |
| Through loss.....(dB): | 4 |
| Return loss: | |
| Input:.....(dB): | > 10 |
| Output | > 10 |
| Outputs..... | 2 |
| Impedance..... (Ohm): | 75 |
| Supply voltage.....(V DC): | 12 or 24 |
| Max supply current | 100 |

Mechanical data:

| | |
|------------------------------------|------------------------------------|
| Dimensions, product.....(mm) (in): | 118 x 67 x 47 (4.65 x 2.40 x 1.73) |
| Dimensions box | None, delivery with UFO or bulk |
| Weight, gross | 138 |
| Connectors | F type |
| DC input | DC-Jack |

DECLARATION OF CONFORMITY

TRIAX confirms that the product conforms to relevant EEC harmonized standards and consequently can carry the CE-mark.

Relevant harmonised standards:

EN55013, EN55020 and EN60065

This document is only valid with the signature of the person responsible for CE-marking by Triax

Date: Signature:

TYPE: **POWER INSERTER**
IFP 529

Date/sign: 07-01-01 LA

PAGE: 1/1

Rev no. : 1
Date/sign: 010104/JES/BR

NO: 339529